

Direct Audio Input Boot with Microphone Switch



■ UE Series



■ UM Series



■ US Series



■ ICON Series

■ Features

- Heavy-duty design
- Conveniently located two-position microphone switch
- Compatible with Unitron direct audio input hearing aids
- Suitable for use with Phonic Ear, Telex, Comtek and other FM systems, lapel microphones and many other audio applications

■ General Applications

Boot Cords: Co-axial (shielded).
Standard connecting plug: 3.5 mm (1/8").

	Monaural	Binaural
Style	Straight	Y-cord
Length	93 cm (37")	80 cm (32")

■ Boot Cords

All our audio boot cords have a 3-pin polarized plug that fits into the boot. The Unitron boot also accepts 3-pin polarized Phonic Ear and Telex cords.

■ Auditory Training/FM Systems

Standard connecting plug to FM systems*:

Right-angle, 2-pin non-polarized plug

Styles: Straight (monaural)

Y-cord (binaural)

Overall Length: 60 cm (24")

Cord: Co-axial (shielded)

Note: When setting our audio boot with FM systems:

- 1) Set hearing aid volume control to the user's typical setting
- 2) Gradually increase FM system volume to the user's comfortable listening level. A typical setting could be very low (1 1/2 - 2)

*Boot cords may not connect to all FM models.

■ Technical Data

Resistance Value:

5.6 k Ohm (Red dot - North America)

470 Ohm (Black dot - Europe)

47 Ohm (Green dot - Europe)

Receptacle:

3-pin polarized plug (Europlug)

Color:

UE Series Beige, brown

UM Series Beige, brown, gray

US Series Beige, brown, gray, taupe

ICON Series beige, brown, gray, taupe

Switch:

two-position Microphone Switch



M=Hearing aid microphone on
(audio input signal and hearing aid microphone function simultaneously)

(M)=Hearing aid microphone off
(audio input signal only)



2300 Berkshire Lane
Plymouth, MN 55441
1 (800) 888-8882
Fax:(763) 557-8828

www.unitronhearing.com